



- ① TWO-WIRE DECODER CONTROLLER:
RAIN BIRD IQ ESP-LXD SATELLITE TWO-WIRE DECODER CONTROLLER WITH IQ CONNECTION MODULE AND IQ NCC RS232 CARTRIDGE IN LXMM METAL CABINET AND LXMPED METAL PEDESTAL. INSTALL CONTROLLER, CABINET AND PEDESTAL PER MANUFACTURER'S RECOMMENDATIONS.
- ② CONCRETE PAD: 6-INCH MINIMUM THICKNESS
- ③ FINISH GRADE
- ④ POWER SUPPLY WIRE
- ⑤ 1-INCH SCH 40 PVC CONDUIT, FITTINGS AND SWEEP ELL TO POWER SUPPLY
- ⑥ COMPACTED SUBGRADE
- ⑦ RS232 SERIAL CABLE TO IQ CENTRAL CONTROL COMPUTER (MAXIMUM LENGTH 50 FEET)
- ⑧ 1-INCH SCH 40 PVC CONDUIT, FITTINGS AND SWEEP ELL FOR RS232 SERIAL CABLE TO IQ CENTRAL CONTROL COMPUTER
- ⑨ PE-CABLE OR Y-CABLE FOR EXTERNAL RADIO TO CLIENT SATELLITE CONTROLLERS
- ⑩ 1-INCH SCH 40 PVC CONDUIT, FITTINGS AND SWEEP ELL FOR COMMUNICATION CABLE TO CLIENT SATELLITE CONTROLLERS
- ⑪ 3-INCH SCH 40 PVC CONDUIT, FITTINGS AND SWEEP ELL FOR TWO-WIRE CABLE
- ⑫ MAXICABLE TWO-WIRE PATH TO DECODERS
USE A DIFFERENT CABLE JACKET COLOR FOR EACH PATH

NOTES:

- 1. IQ ESP-LXD CONTROLLER COMES WITH 50 STATIONS AVAILABLE. TWO ADDITIONAL 75 STATION ESPLXD-SUM75 MODULES MAY BE ADDED TO EXPAND THE CONTROLLER UP TO 200 TOTAL STATIONS.
- 2. PROVIDE PROPER GROUNDING COMPONENTS TO ACHIEVE GROUND RESISTANCE OF 10 OHMS OR LESS.
- 3. USE PE-CABLE WITH SHORT HAUL MODEMS FOR INSTANCES WHERE CONTROLLER IS MORE THAN 50 FEET FROM IQ CENTRAL CONTROL COMPUTER.

IQ ESP-LXD SATELLITE TWO-WIRE DECODER CONTROLLER WITH IQ CONNECTION MODULE

1-10-11

D

N.T.S.

AND IQ NCC RS232 CARTRIDGE IN METAL PEDESTAL